



19.95 EUR
incl. 19% VAT, plus [shipping](#)

Spannungswandler 150W Continous- /450W Peak-Power SOFTSTART

You only have to connect this power inverter to your cigarette lighter and then you have an regular 230V power outlet, where you can stick in your favorite devices like TV set or computers.

This inverter is fanless and therefore can be hidden easily.

Technical Specifications

| | | | |
|----------------------|------------------|--------------------------|----------------------|
| DC Input Voltage | 12V (10-15V) | No load current | < 0.42A |
| Surge Power Capacity | 450W | Battery low alarm | DC 10.5 +/- 0.5V |
| Efficiency | over 90% | Battery low shutdown | DC 10 +/- 0.5V |
| Dimensions | 165 x 91 x 58 mm | | |
| Weight | 0.85 kg | Alarm & thermal shutdown | 60 +/- 5 deg Celsius |